


BOSCH

Invented for life

LBB 4560 Charging Units



- ▶ Can accommodate 56 receivers
- ▶ Universal mains power facility allows use worldwide
- ▶ Rapid recharging: within 1 hour and 45 minutes

The charging units are used for charging and storing the LBB 4540 Pocket Receivers.

Functions

Controls and Indicators

- On/off switch
- Charging status indication on the receivers

Interconnection

- Mains input with loop-through facility; male and female Euro mains socket
- 56 charging contacts. Compatible with LBB 4540 receivers

Parts Included

Quantity	Component
1	LBB 4560 Charging Unit
1	Mains cable

Technical Specifications

Electrical

Mains voltage	90 to 260 V, 50 to 60 Hz
Power consumption	270 W (56 receivers charging)
Power consumption (standby)	17 W (no receivers in the charging unit)

Mechanical

Mounting	
LBB 4560/50	Screws and plugs for wall mounting included
Dimensions (H x W x D)	
LBB 4560/00	230 x 690 x 530 mm (9 x 27 x 21 in)
LBB 4560/50	130 x 680 x 520 mm (5 x 27 x 20 in)
Weight excl. receivers	
LBB 4560/00	15.5 kg (34 lb)
LBB 4560/50	11.2 kg (25 lb)
Weight incl. 56 receivers	
LBB 4560/00	22.3 kg (49 lb)
LBB 4560/50	18.0 kg (40 lb)
Color	Charcoal with grey

Ordering Information

LBB 4560/00 Charging Case
for portable use

Ordering Information

LBB 4560/50 Charging Cabinet
for fixed installation

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Bosch Security Systems Pte Ltd
38C Jalan Pemimpin
Singapore 577180
Phone: +65 6319 3450
Fax: +65 6319 3499
apr.securitysystems@bosch.com
www.boschsecurity.com

Represented by